



#### POWERED BY:



Generating Set pictured may include optional accessories

#### GENERATING SET MODEL (JP200)

Output Ratings	Prime	Standby
380-415 V, 3 ph, 50 Hz, 1500 rpm	200 KVA 160 KW	220 KVA 176 KW
480 V, 3 ph, 60 Hz, 1800 rpm	248 KVA 198 KW	273 KVA 218 KW

Applicable Voltages: 220/127 V at 60 Hz only (Consult your dealer for more details)

#### ENGINE / TECHNICAL DATA

Engine Make	Perkins		
Engine Model	1506A-E88TAG1		
Governing Type	Electronic		
Number of Cylinders	6		
Cylinder Arrangement	Vertical in line		
Bore and Stroke mm	112 x 149		
Displacement / Cubic Capacity litres	8.8		
Induction System	Turbocharged, air to air charge cooled		
Cycle	4 stroke		
Combustion System	Direct Injection		
Compression Ratio	16.1:1		
Rotation	Anti-clockwise, viewed on flywheel		
Cooling System	Water - cooled		
Frequency and Engine Speed	50Hz & 1500rpm		60Hz & 1800rpm
	Prime	Standby	Prime Standby
Gross Engine Power kW	192	210	233 255
Fuel Consumption @ 50% load L/hr	24	-	29.3 -
@ 75% load L/hr	33.9	-	41.6 -
@ 100% load L/hr	44.6	47.2	54.2 59.5
Total Lubrication System Capacity litres	41	41	41 41
Total Coolant Capacity litres	29.6	29.6	29.6 29.6
Exhaust Temperature: °C	458	470	431 444
Radiator Cooling Air Flow (Min): m <sup>3</sup> /sec	6.16	6.16	8.0 8.0
Combustion Air Flow: m <sup>3</sup> /min	12.8	13.5	17.7 18.6
Exhaust Gas Flow: m <sup>3</sup> /min	30.2	31.9	39.7 42.1
Fuel Tank Capacity: litres	360	360	360 360
Boost Pressure Ratio	2.5	2.7	3.1 3.2

#### DIMENSIONS AND WEIGHT

Length cm	Width cm	Height cm	Weight* kg (wet)
280	99	174	2052

\* For skid mounted genset without enclosure

wet weight = with lube oil and coolant

#### STANDARD SPECIFICATIONS

##### 1. ENGINE

Perkins four stroke heavy duty high performance industrial type diesel engine.

##### 2. ENGINE FILTRATION SYSTEM

- Cartridge type dry air filter.
- Cartridge type fuel filter.
- Full flow lube oil filter.
- Water filter.

All filters have replaceable elements.

##### 3. COOLING RADIATOR

Radiator and cooling fan, complete with safety guards, designed to cool the engine at high ambient temperatures (consult your dealer for de-rating factors)

##### 4. EXHAUST SYSTEM

Heavy duty Industrial Exhaust Silencer

Silencer noise reduction level	12 (dB)
Maximum allowable back pressure	10 (kPa)

##### 5. CIRCUIT BREAKER TYPE

ABB 3 pole MCCB. (4 pole is optional)

(contd.)

#### ALTERNATOR DATA

Make	Leroy Somer
Model	LSA46.2M5
No. of bearings	1
Insulation class	H
Total Harmonic Content	<2.5%
Wires	12
Ingress Protection	IP23
Excitation System	SHUNT
Winding Pitch	2/3 (n° 6)
AVR Model	R250
Overspeed	2250 mn <sup>-1</sup>
Voltage Regulation (steady)	± 0.5%
Short Circuit Capacity	-

AREP & PMG Excitation System Available as Optional.

#### CONTROL PANEL

Make	Deep Sea
Model	DSE6110

The DSE6110 is an Auto Start Control Module for single genset applications. It includes a backlit LCD display which clearly shows the status of the engine all the times. This module can either be programmed using the front panel or by using the DSE configuration suite PC software.

##### Metering and Alarm indications:

- Generator frequency
- Underspeed, Overspeed
- Generator volts (L-L, L-N)
- Generator current
- Engine oil pressure
- Engine coolant temperature
- Fuel level (Warning or shutdown) - Optional
- Hours run counter
- Battery volts
- Fail to start/stop
- Emergency stop
- Failed to reach loading voltage/frequency
- Charge fail
- Loss of magnetic pick-up signal - Optional
- Low DC voltage
- CAN diagnostics and CAN fail/error

(Please refer to DSE6110 brochure for more details)

**AN INSPIRED DESIGN TO MEET YOUR NEEDS**



Generating Set pictured may include optional accessories

### RATINGS DEFINITION

#### Prime Power

These ratings are applicable for supplying continuous electrical power (at variable load) in lieu of commercially purchased power. 10% overload power is available for 1 hour in 12 hours continuous operation.

#### Standby Power

These ratings are applicable for supplying continuous electrical power (at variable load) in the event of a utility power failure. No overload is permitted on these ratings.

### STANDARD REFERENCE CONDITIONS

Output ratings are presented at 25°C air inlet temperature, barometric pressure 100 kPa, relative humidity 30%. This generating set is designed to operate at high ambient temperatures (up to 55°C), humidity (up to 99%) and higher altitudes. De-rating may apply, please consult your dealer for specific site ratings.

Some of the specifications are not standard on all Genset models.

### AVAILABLE OPTIONS & ACCESSORIES

We offer a range of optional features and accessories to tailor our generating sets to meet your power needs.

#### OPTIONS

- A variety of generating set control and synchronizing panels
- Additional protection alarms and shutdowns
- Water fuel separator
- Water jacket heater
- Battery charger

#### ACCESSORIES

- Genuine spare parts
- Load banks
- Auxiliary fuel tanks
- Manual & automatic transfer switches

Distributed and Serviced by:



For further information on all of the standard and optional features accompanying this product please contact your local dealer or visit [www.JubailiBros.com](http://www.JubailiBros.com)



JET Generators are assembled  
in facilities certified to ISO 9001

All information in this document is substantially correct  
at time of printing and may be altered subsequently.

## STANDARD SPECIFICATIONS

### 6. FUEL SYSTEM

On Generating Sets up to 700 KVA, the baseframe design is incorporated with an integral fuel tank with a capacity of approx. 8 hours running at Full Load. The tank is supplied complete with fill cap breather, fuel feed and return lines to the Engine and drain plug.

### 7. ALTERNATOR

#### 7.1 INSULATION SYSTEM

- The insulation system is Class H.
- All windings are impregnated in either a triple dip thermosetting liquid, oil and acid resisting polyester varnish or vacuum pressure impregnated with a special polyester resin.
- Heavy coat of antitracking varnish additional protection against moisture or condensation.

#### 7.2 AUTOMATIC VOLTAGE REGULATOR (AVR)

The fully sealed Automatic Voltage Regulator maintains the Voltage Regulation at  $\pm 0.5\%$ . Nominal adjustment by means of a trim pot incorporated on the AVR.

#### 7.3 MOTOR STARTING

An overload capacity equivalent to 300% of the Full Load impedance at zero Power Factor can be sustained for 10 seconds, when AREP or PMG option is fitted.

### 8. MOUNTING ARRANGEMENT

#### 8.1 BASE FRAME

The complete Generating Set is mounted as a whole on a heavy duty fabricated steel Baseframe.

#### 8.2 COUPLING

The Engine and Alternator are directly coupled by means of an SAE flange. The Engine flywheel is flexibly coupled to the Alternator rotor.

#### 8.3 ANTI-VIBRATION MOUNTING PADS

Anti-Vibration pads are affixed between the Engine / Alternator feet and the Baseframe thus ensuring complete vibration isolation of the rotating assembly.

#### 8.4 SAFETY GUARDS

The Fan & Fan Drive along with the Battery Charging Alternator are Safety Guard protected for personnel protection.

### 9. FACTORY TESTS

- The Generating set is load tested before dispatch
- All protective devices control functions and site load conditions are simulated. The generator and it's systems are checked before dispatch.

### 10. EQUIPMENT FINISHING

All mild steel components are fully degreased and painted with powder coated paint to ensure maximum scuff resistance and durability.

### 11. DOCUMENTATIONS

Operation & Maintenance manual, Circuit wiring diagrams and Commissioning / Fault Finding instruction leaflets are accompanied with the Generator.

### 12. QUALITY STANDARDS

The equipment meets the following standards: BS4999, BS5000, BS5514 IEC 60034, VDE0530, NEMA MG 1.22 and ISO 8528.

### 13. WARRANTY

All of the Generating Sets are covered under a warranty policy for a period of 12 months. Warranty of the equipment is in line with manufacturers warranty terms & conditions.

(check warranty statement for more details, as it may vary for different countries)

In line with continuous product development, we reserve the right to change specifications without notice.