




JGP2000 / JGP2200E



GENSET MODEL

| | Prime | JGP2000 | |
|-------------------------------|-----------|--------------|------------|
| | Standby | JGP2200E | |
| Engine speed | rpm | 1500 | 1800 |
| Frequency | Hz | 50 | 60 |
| Prime power | KVA KW | 2000 1600 | N/A N/A |
| Standby power | KVA KW | 2200 1760 | N/A N/A |
| Gross Engine Power | KW hp | 1937 2597 | N/A N/A |
| * Ratings at 0.8 Power Factor | | | |
| Fuel consumption @50% load | L/hr | 213 | N/A |
| @75% load | L/hr | 313 | N/A |
| @100% load | L/hr | 423 | N/A |

TECHNICAL DATA

| | | |
|------------------------------|------------|------|
| Perkins Engine Model | 4016TAG2A | |
| Leroy Somer Alternator Model | LSA51.2M60 | |
| Number of Cylinders | 16 / Vee | |
| Cubic Capacity | Litres | 61.1 |
| | cu.in | 3730 |
| Bore | mm | 160 |
| | in | 6.3 |
| Stroke | mm | 190 |
| | in | 7.5 |
| Fuel Tank Capacity | Lit | N/A |

DIMENSIONS & WEIGHT

| | | |
|--------|----|-------|
| Length | cm | 572 |
| Width | cm | 230 |
| Height | cm | 302 |
| weight | Kg | 15700 |

Prime rating: These ratings are applicable for supplying continuous electrical power in lieu of commercially purchased power. This model can supply 10% overload power for 1 hour in 12 hours

Standby Rating: These ratings are applicable for supplying continuous electrical power (at variable load) in the event of utility power failure. No overload is permitted on these ratings

Headquarter
Jubaili Bldg,
Maarouf Saad Boulevard
P.O. Box 60, Sidon, Lebanon
Tel: +961 7 730871
www.JubailiBros.com

