



JGP13/JGP15



GENSET MODEL

	Prime	JGP13	
	Standby	JGP15	
Engine speed	rpm	1500	1800
Frequency	Hz	50	60
Prime power	KVA KW	13 10.4	15 12
Standby power	KVA KW	14.3 11.4	16.5 13.2
Gross Engine Power	KW hp	13.5 18	16.2 22

*Ratings at 0.8 Power Factor

Fuel consumption @50% load	L/hr	2.1	2.4
@75% load	L/hr	2.8	3.2
@100% load	L/hr	3.7	4.3

TECHNICAL DATA

Perkins Engine Model	403D-15G	
Leroy Somer / Stamford Alternator Model	LSA40VS2 / PI044F	
Number of Cylinders	3 in line	
Cubic Capacity	Litres	1.5
	cu.in	91.3
Bore	mm	84
	in	3.3
Stroke	mm	90
	in	3.5
Fuel Tank Capacity	Lit	40

DIMENSIONS & WEIGHT

Length	cm	125
Width	cm	52
Height	cm	117
weight	Kg	400

Prime rating: These ratings are applicable for supplying continuous electrical power in lieu of commercially purchased power. This model can supply 10% overload power for 1 hour in 12 hours.

Standby Rating: These ratings are applicable for supplying continuous electrical power in the event of utility power failure. No overload is permitted on these ratings

Headquarter
Jubaili Bldg,
Maarouf Saad Boulevard
P.O. Box 60, Sidon, Lebanon
Tel: +961 7 730871
www.JubailiBros.com

