



## JGP250H2 / JGP275HE2



### GENSET MODEL

	Prime	JGP250H2	
	Standby	JGP275HE2	
Engine speed	rpm	1500	1800
Frequency	Hz	50	60
Prime power	KVA KW	250 200	N/A N/A
Standby power	KVA KW	275 220	N/A N/A
Gross Engine Power	KW hp	250.9 336	N/A N/A
* Ratings at 0.8 Power Factor			
Fuel consumption @50% load	L/hr	31.1	N/A
@75% load	L/hr	46.1	N/A
@100% load	L/hr	58.9	N/A

### TECHNICAL DATA

Perkins Engine Model	1306C-E87TAG6	
Leroy Somer / Stamford Alternator Model	LSA46.2L6/UCD274K	
Number of Cylinders	6 in line	
Cubic Capacity	Litres	8.7
	cu.in	531
Bore	mm	116.6
	in	4.6
Stroke	mm	136
	in	5.4
Fuel Tank Capacity	Lit	385

### DIMENSIONS & WEIGHT

Length	cm	290
Width	cm	99
Height	cm	170
weight	Kg	2252

**Prime rating:** These ratings are applicable for supplying continuous electrical power in lieu of commercially purchased power. This model can supply 10% overload power for 1 hour in 12 hours

**Standby Rating:** These ratings are applicable for supplying continuous electrical power in the event of utility power failure. No overload is permitted on these ratings

Headquarter  
Jubaili Bldg,  
Maarouf Saad Boulevard  
P.O. Box 60, Sidon, Lebanon  
Tel: +961 7 730871  
www.JubailiBros.com

